

DM-232 (RS232 PEA)

The Ikon DM-232 splitter is used to split a single RS232 transmitter to feed two receivers. It's typically used when two identical displays are to be controlled from a single RS232 output.



Connections

- POWER** 12V DC power input normally looped from the main controller. You can also use a 15V or 24V supply.
- RS232** Connect the TX and Ground from the controller to the IN and COM terminals
- RS232 OUT** Connect the Out 1 or Out 2 and associated COM to the RX and Ground of the devices to be controlled.

Please ensure that all connections are via the screw terminals only. Use a 1.6mm (max 1.8mm) flat bladed screwdriver.

The base of the unit allows standard DIN rail mounting.

There are no software requirements for operation.

A four output version is also available and units can be cascaded for more outputs.